

Entec 15kV, 27kV & 38kV 630A Automatic Recloser



Solid Insulated Pole Mount Auto Recloser with Vacuum Interruption

- ✓ Vacuum technology, no SF6 or Oil
- ✓ EPR-1 Rated 15.5kV, 630A, 110kV BIL – **Ex Stock**
- ✓ EPR-2 Rated 27kV, 630A, 150kV BIL – **Indent Only**
- ✓ EPR-3 Rated 38kV, 800A, 170kV BIL – **Indent Only**
- ✓ Manual trip and lockout via hot stick
- ✓ Pole mount brackets available
- ✓ Multifunction control with integral RTU
- ✓ Built in Source side CT's & VT's
- ✓ Built in Load side VT's. Optional External Sensor on EPR-3
- ✓ Outdoor rated cycloaliphatic resin
- ✓ Stainless steel mechanism box and control cabinet
- ✓ Low maintenance
- ✓ Scada kit options
- ✓ Entec reliability

AUCKLAND
8 BEATRICE TINSLEY CRES
ROSEDALE 0632
PO BOX 302-248, NORTH HARBOUR
AUCKLAND 0751
T: (09) 444 2350 F: (09) 444 3085

HAMILTON
1/21 RAILSIDE PLACE
DINSDALE 3204
PO BOX 230
FRANKTON 3242
T: (07) 846 0602 F: (07) 846 0604

WELLINGTON HEAD OFFICE
137 THORNDON QUAY
WELLINGTON 6011
PO BOX 3749
WELLINGTON 6140
T: (04) 472 7614 F: (04) 472 7658

CHRISTCHURCH
UNIT 4, 89 VICKERYS ROAD
WIGRAM 8042
PO BOX 11 033, SOCKBURN
CHRISTCHURCH 8443
T: (03) 379 2628 F: (03) 379 2627

EPR Automatic Recloser

Description	EPRIS (1phase)	EPR-1 (3phase)	EPR-2 (3phase)	EPR-3 (3phase)
Stock or Indent	Indent Only	Ex Stock	Indent Only	Indent Only
Maximum System Voltage	15.5kV	15.5kV	27kV	38kV
Rated Frequency	50/60Hz	50/60Hz	50/60Hz	50/60Hz
Rated Continuous Current	630A	630A	630A*	800A
Rated Short Circuit Interruption Current	16kA	16kA	12.5kA	16kA
Rated Making Current	41.6kA (peak value)	41.6kA (peak value)	41.6kA (peak value)	41.6kA (peak value)
Power Frequency Withstand Voltage				
- Dry	50kV (1 min)	50kV (1 min)	60kV (1 min)	70kV (1 min)
- Wet	45kV (10 sec)	45kV (10 sec)	50kV (10 sec)	60kV (10 sec)
Rated Impulse Withstand Voltage	110kV BIL	110kV BIL	150kV BIL	170kV BIL
Mechanical Operation Life	10,000 Operations	10,000 Operations	10,000 Operations	10,000 Operations
Actuator Operation Power	DC120V	DC120V	DC120V	DC120V
Auxiliary Power Supply For the Control	AC 110V to 240V	AC 110V to 240V	AC 110V to 240V	AC 110V to 240V
Control Circuit Voltage	DC 24V	DC 24V	DC 24V	DC 24V
Protection Current Transformer (CT) ratio	1000:1 A	1000:1 A	1000:1 A	1000:1 A
Weight				
- Main Tank	40kg	130kg	160kg	185kg
- Control Cubicle	84kg	84kg	84kg	85kg

Microprocessor Based Recloser Control - ETR300-R

- Analysis of current/voltage normal & negative sequence for power quality monitoring.
- Recording of PQM with fault waveform of 128 sampling and 20 cycles.
- Harmonics analysis of electric data. (THD/TDD content ratio)
- Monitoring of Sag, Swell, Interruption, over & low voltage, unbalance and etc.
- Improvement of fault detection algorithm
- Automatic isolation of faulted section site and interconnection with other healthy section.
- Improved measuring accuracy
- Time synchronization and Position Information by GPS support
- Multi-Protocol support. (DNP3.0, MODBUS, IEC60870-5-101/104 & IEC61850)
- User programmable logic(PLC) support

